Actual

 ϵ

Product Size Shown

SENSORS

Low & High Frequency Accelerometer, Top Exit Connector, 1000 mV/g



Product Features


Designed for low speed Rotors, Wind Turbine Main Bearings, and Gear Box Inputs, but can also be used for High Frequency Detection.

Can be used with any application that requires low and high frequency measurements.

- 1000 mV/g Sensitivity, ±5% Sensitivity
- 0.1 Hz for Low Frequency Measurements
- 10,000 Hz for High Frequency Detection







Specifications	Standard	Metric
Part Number	AC214	M/AC214
Sensitivity (±5%)	1000 mV/g	
Frequency Response (±3dB) Frequency Response (±10%)	6-600,000 CPM 18-480,000 CPM	0,1-10000 Hz 0,3-8000 Hz
Dynamic Range	± 7 g, peak	
Electrical		
Settling Time	<2 Seconds	
Voltage Source (IEPE)	18-30 VDC	
Constant Current Excitation	2-10 mA	
Spectral Noise @ 10 Hz	1.3 μg/√Hz	
Spectral Noise @ 100 Hz	0.2 μg/√Hz	
Spectral Noise @ 1000 Hz	0.1 μg/√Hz	
Output Impedance	<100 ohm	
Bias Output Voltage	10-14 VDC	
Case Isolation	>10 ⁸ ohm	

Specifications	Standard	Metric	
<u>Environmental</u>			
Temperature Range	-58 to 250°F	-50 to 121°C	
Maximum Shock Protection	5,000	5,000 g, peak	
Electromagnetic Sensitivity	(CE	
Sealing	Welded,	Welded, Hermetic	
<u>Physical</u>			
Sensing Element	PZT C	PZT Ceramic	
Sensing Structure	Shear	Shear Mode	
Weight	3.25 oz	92 grams	
Case Material	316L Stai	316L Stainless Steel	
Mounting	1/4	1/4-28	
Connector (non-integral)	2 Pin MI	2 Pin MIL-C-5015	
Resonant Frequency	1,080,000 CPM	18000 Hz	
Mounting Torque	2 to 5 ft. lbs.	2,7 to 6,8 Nm	
Mounting Hardware	1/4-28 Stud	M6x1 Adapter Stud	
Calibration Certificate	C	CA10	

Ordering Information

