Actual

 ϵ

Product Size Shown

Low & High Frequency Accelerometer, Top Exit Connector, 250 mV/g




Product Features


Designed for low speed Rotors, Wind Turbine Main Bearings, and Gear Box Inputs, but can also be used for High Frequency Detection.

Can be used with any application that requires low and high frequency measurements.

- 250 mV/g Sensitivity, ±10% Sensitivity
- 0.2 Hz for Low Frequency Measurements
- 10,000 Hz for High Frequency Detection







Specifications	Standard	Metric	
Part Number	AC212	M/AC212	
Sensitivity (±10%)	250 m	ıV/g	
Frequency Response (±3dB) Frequency Response (±10%)	12-600,000 CPM 18-420,000 CPM	0,2-10000 Hz 0,3-7000 Hz	
Dynamic Range	± 30 g, peak		
Electrical			
Settling Time	<2 Seconds		
Voltage Source (IEPE)	18-30	VDC	
Constant Current Excitation	2-10	mA	
Spectral Noise @ 10 Hz		2.0 μg/√Hz	
Spectral Noise @ 100 Hz	0.52 μg	ı/√Hz	
Spectral Noise @ 1000 Hz	al Noise @ 1000 Hz 0.12 μg/√Hz		
Output Impedance	<100 ohm		
Bias Output Voltage	10-14	VDC	
Case Isolation	>108 0	ohm	

Specifications	Standard	Metric		
Environmental				
Temperature Range	-58 to 250°F	-50 to 121°C		
Maximum Shock Protection	5,000	5,000 g, peak		
Electromagnetic Sensitivity		CE		
Sealing	Welded, Hermetic			
<u>Physical</u>				
Sensing Element	PZT Ceramic			
Sensing Structure	Shear Mode			
Weight	3.25 oz	92 grams		
Case Material	316L Stai	316L Stainless Steel		
Mounting	1/	1/4-28		
Connector (non-integral)	2 Pin MIL-C-5015			
Resonant Frequency	1,080,000 CPM	18000 Hz		
Mounting Torque	2 to 5 ft. lbs.	2,7 to 6,8 Nm		
Mounting Hardware	1/4-28 Stud	M6x1 Adapter Stud		
Calibration Certificate	С	CA10		

Ordering Information

	•				
Standard	AC212-1D (1/4-28 Stud) Stock Product	AC212-2D / (1/4-28 Stud) Build To Order	(length in feet)	(termination)	AC212-3D / / (1/4-28 Stud) / (cable length in feet) - (termination)
Metric	M/AC212-1D (M6x1 Adapter Stud) Stock Product	M/AC212-2D / (M6x1 Adapter Stud) Build To Order	(length in feet)	(termination) M - (termination)	M/AC212-3D / / - - -