PRO 25 mm, 4-20 mA Output, Driver Assembly



Panel Mount Option (Shown Above)

TERMINAL BLOCK WIRING

Connections	Functions
-	4-20 mA Supply
+	4-20 mA DC Gap
Com	
Vout	-20 mV/mil, DC Gap



Product Features •

Driver assembly DD100870 offers multiple options for mounting and easy connections via BNC jack and screw terminals.


(Shown Above)

- Flexible system configuration
- 4-20 mA current loop provides power to the driver, and a displacement output proportional to the DC gap
- -20 mV/mil (-0.787 V/mm) output available at terminal block (Vout & Com) and at the BNC
- Multiple mounting options (DIN rail, panel or none)

Specifications -

Temperature Range: -49°F (-45°C) to 185°F (85°C) Linear Range: 25 to 525 mils (.63 - 13.33 mm) @ approximately 4-20 mA Nominal Voltage Output: -20 mV/mil (-0.787 V/mm) 4-20 mA Output: Proportional to the DC gap Input Power/Voltage: 17.5 VDC to 30 VDC (Loop Powered) Aluminum enclosure Miniature 12-32 threaded connector 4 position screw terminals + BNC output

Ordering Information





Example Part Number: DD100870-91-00 4140 Steel, 9 meter system length, DIN mount, CE certified