
# BENTLY™ 3300/3300XL COMPATIBLE 11 mm, 4-20 mA Output, Driver Assembly



Panel Mount Option (Shown Above)

#### **TERMINAL BLOCK WIRING**

Connections	Functions
-	4-20 mA Supply
+	4-20 mA DC Gap
Com	
Vout	-100 mV/mil, DC Gap



Certified

Panel Mount Option (Shown Above)

#### **Product Features -**


Driver assembly DX330770 offers multiple options for mounting and easy connections via BNC jack and screw terminals.

- Flexible system configuration
- 4-20 mA current loop provides power to the driver, and a displacement output proportional to the DC gap
- -100 mV/mil (-3.94 V/mm) output available at terminal block (Vout & Com) and at the BNC
- Multiple mounting options (DIN rail, panel or none)

### Specifications -

Temperature Range: -31°F (-35°C) to 185°F (85°C)
Linear Range: 20 to 180 mils (0.5 - 4.5 mm) @ approximately 4-20 mA
Nominal Voltage Output: -100 mV/mil (-3.94 V/mm)
4-20 mA Output: proportional to the DC gap
Input Power/Voltage: 17.5 VDC to 30 VDC (Loop Powered)
Aluminum enclosure
Miniature 12-32 threaded connector
4 position screw terminals + BNC output
Calibrated to AISI 4140 steel

## **Ordering Information**





Example Part Number: DX330770-91-00 4140 Steel, 9 meter system length, DIN mount, CE certified